

## Dear Customer

### ◆ About the Upgrade of the DC-GH5S Firmware

The following functions were added or changed from Ver. 1.1 of the firmware.


Please read this in conjunction with the owner's manual for the camera.



- The firmware version can be checked from the [Version Disp.] of the [Setup] menu.

**[L.Monochrome D] has been added to [Photo Style] in the [Rec] menu.**

Applicable modes:   **P** **A** **S** **M**  

**MENU** →  **[Rec]** → **[Photo Style]**

 <b>[L.Monochrome D]</b>	Monochrome effect that creates a dynamic impression with enhanced highlights and shadows.
--	---

- You can adjust the following picture quality settings:
  - [Contrast]/[Sharpness]/[Noise Reduction]/[Color Tone]/[Filter Effect]/[Grain Effect]
- The Auto Focus Mode [] operates in the same way as [].


**The [Grain Effect] picture quality adjustment has been added to [Photo Style] in the [Rec] menu.**

Applicable modes:   **P** **A** **S** **M**  

#### 1 Select the menu.

**MENU** →  **[Rec]** → **[Photo Style]** →  
**[Monochrome]/[L.Monochrome]/[L.Monochrome D]**

#### 2 Press ▲/▼ to select [Grain Effect], and then press ◀/▶ to adjust.

 <b>[Grain Effect]</b>	[Low]/ [Standard]/ [High]	Sets the grain effect level.
	[Off]	—

#### 3 Press [MENU/SET].

- The effect of [Grain Effect] cannot be checked on the recording screen.
- [Grain Effect] is not available in the following cases:
  - When recording motion pictures
  - When recording 4K photos
  - When recording with the Post Focus function
- If you set [Grain Effect], Auto Review will not be displayed when recording with [Time Lapse Shot] or [Stop Motion Animation].

**[Focus Ring Lock] has been added to the [Custom] menu.**


This disables the focus ring operation of the interchangeable lens during Manual Focus to lock the focus.

**MENU** →  **[Custom]** →  **[Operation]** → **[Focus Ring Lock]**

**Settings: [ON]/[OFF]**

- [MFL] is displayed on the recording screen while the focus ring is locked.

**[WB/ISO/Expo. Button] has been added to the [Custom] menu.**

This sets the operation to be performed when [WB] (White Balance), [ISO] (ISO sensitivity) or [] (Exposure Compensation) is pressed.

**MENU** →  **[Custom]** →  **[Operation]** → **[WB/ISO/Expo. Button]**

<b>[While Pressing]</b>	Allows you to change the setting while pressing and holding the button.
<b>[After Pressing]</b>	Allows you to change the setting after pressing the button.

**[Dial] has been added to [Operation Lock Setting] in the [Custom] menu.**

**MENU** →  **[Custom]** →  **[Operation]** → **[Operation Lock Setting]**

<b>[Dial]</b>	Disables the front, rear, and control dial operations.
---------------	--



- Press the function button assigned with [Operation Lock] to disable the operations.

**Items that can be assigned to the function buttons have been added.**

**MENU** →  **[Custom]** →  **[Operation]** → **[Fn Button Set]** →  
**[Setting in REC mode]**

– [Focus Ring Lock]	– [Sound Rec Level Disp.]
– [E-Stabilization (Video)]	– [L.Monochrome D]

- [Focus Ring Lock] can also be set by using [Lens Fn Button Setting].



**MENU** →  **[Custom]** →  **[Lens / Others]** → **[Lens Fn Button Setting]**

**Pictures in a group can now be selected for RAW processing.**

**MENU** →  **[Playback]** → **[RAW Processing]**



#### 1 Press ◀/▶ to select a picture group.

#### 2 Press ▼.

- You can perform the same operation by touching [], etc.
- To return to the picture selection screen, press ▼ again, or touch [].



**The screen icons for the Image Stabilizer have been modified.**

[] ([Normal]) or [] ([Panning]) is displayed on the recording screen, depending on the [Stabilizer] setting in the [Rec] menu.

**About the “LUMIX Tether” software**

LUMIX Tether Ver. 1.3 or higher is required to connect to a camera with updated firmware.

Check the site below to download and install the software.

[http://panasonic.jp/support/global/cs/soft/download/d\\_lumixtether.html](http://panasonic.jp/support/global/cs/soft/download/d_lumixtether.html)